

# RHINO T100



## At a glance

Android 13.0

[Android 13 \(Coming Soon!\)](#)

3GB RAM

32GB Storage

Global LTE

EMM validated

## Getting started

Doc	Description
Quickstart	Get started with your device quickly
Device manual	Learn how to use your T100 in detail

## Device spec

<b>Display</b>	10.1" HD 164 PPI TFT LCD with IPS panel Brightness up to 380cd/m2 1280x800 resolution Viewing angles 80°/80°(v/h) 16.7m colours 16:10 aspect ratio 60Hz refresh rate 5 touch points
<b>Memory &amp; storage</b>	3GB 32GB
<b>Processor</b>	Snapdragon 680 SM6225 Octacore 2.4GHz
<b>Battery</b>	6000mAh Li-ion Quick Charge 2.0, 18W 44 hours typical use 16 days standby

<b>SIM</b>	Nano-SIM & eSIM
<b>Ports</b>	SIM MicroSD up to 1TB USB Type C, USB 2.0 3.5mm jack
<b>Audio</b>	Microphone Stereo Speaker
<b>Connectivity</b>	LTE Cat 4 3G: 1 2 4 5 4G: 1 2 3 4 5 7 12 13 14 17 18 19 20 25 26 29 30 41 66 71 Wi-Fi 802.11 a/b/g/n/ac Bluetooth 5.1 NFC Location: GPS, A-GPS, Galileo, QZSS
<b>Camera</b>	5MP AF front 8MP FF rear
<b>Sensors</b>	Accelerometer eCompass Ambient light sensor Proximity sensor SAR
<b>Environmental</b>	Functional up to 95% humidity 0c to 40c typical operating temp Unboxed(LHW): 205.8mm x 128mm x 9.8mm IP52 rated 0.5m drop-tested
<b>Certifications</b>	FCC CE UKCA PTCRB Google Play Protect AT&T Network Optimized AT&T FirstNet Ready

## Product lifecycle

For product support and lifecycle status, please see the [security](#) page.

## Warranty information

All RHINO hardware comes with a 1 year limited warranty. For detailed warranty information, please see [RHINO Warranty](#).